How to configure PPPoE with the Mac Pro

1. Go to the Apple menu and choose System Preferences.



2. Double-click the Network icon in the Internet & Wireless section.



3. In the left-hand panel you will see listed Ethernet, AirPort, etc. Click the "+" sign under that panel.

	Location:	Automatic	
Ethernet Connected	<->	Status:	Connected
AirPort On	1		Ethernet is currently active and has the IP address 192.168.1.2.
FOMA L05A 2 Not Configured	C	Configure IPv4:	Using DHCP
FOMA····手動作成	Que	IP Address:	192.168.1.2
Not Connected	6	Subnet Mask:	255.255.255.0
FireWire Not Connected	Y	Router:	192.168.1.1
		DNS Server:	192.168.1.1
		Search Domains:	
		IPv6 Address:	2001:c90:93c:1003:226:b0ff:feed:48
			<u></u>

4. In the window that appears, supply the following information:

Interface	PPPoE
Ethernet	Ethernet
Service Name	IAUPR Apartments

Click the **Create** button

A connection called **IAUPR Apartments** connection will be added to the left-hand panel.

Loc	ation: Automatic		
ASAHI-Net Not Connected	Status:	Not Configured	
Ethernet Connected	-		
AirPort	PPPoE Service Name:	IAUPR Apartments	
FOMA LOSA 2	Account Name:	O87654321	1
Not Configured	Password:		
Not Connected		Remember this password	4
FireWire Not Connected		Connect	
	Show PPPoE status	in menu bar	vanced)

5. Click on the IAUPR Apartments entry and supply the following information:

PPPoE Service Name	IAUPR Apartments
Account Name	Your IAUPR Apartments User ID followed * Enter your User name as written E.g. 0876546321
Password	The password for your IAUPR Apartments ID * Enter your Password as written
Remember this password	CHECK THIS
Show PPPoE status in menu bar	CHECK THIS



6. Click the Apply button.



7.Click the Connect button.



8. A connection should now be established between your computer and the Internet. Open a Web browser and start viewing Web pages.

Loc	ation: Automatic	
ASAHI-Net Connected Ethernet Connected AirPort Connected FOMA LOSA 2 Not Configured FOMA…動作成 Not Connected FireWire Not Connected	Status: Connected Connect Time: 00:08:45 IP Address: Provided by Account Name: 08765432 Password: Remembe Disconnect	Sent: 0000000000 Received: 0000000000 ISP when required 1 1 r this password
- ••	Show PPPoE status in menu bar	Advanced)

9. Another way to connect or disconnect is to use the <***>icon in the menu bar and choose to connect or disconnect from the Internet.

